

# Product data sheet

Specifications



## Blind / switch actuator REG-K/12x/24x/10 with manual mode, light grey

MTN649912

⚠ Discontinued on: 14 July 2021

⚠ Discontinued

### Main

Range of product	KNX
Product or component type	Blind switch actuator
Operating mode	KNX bus system Manual
Bus type	KNX

### Complementary

Total number of 18 mm modules	12
Mounting support	DIN rail
[Ue] rated operational voltage	100...240 V AC 50...60 Hz
[In] rated current	10 A
Number of outputs	12
Load type	Motor: 434 W, 100 V AC Motor: 1000 W, 230 V AC Motor: 1043 W, 240 V AC Incandescent lamps: <= 869 W, 100 V AC Incandescent lamps: <= 2000 W, 230 V AC Incandescent lamps: <= 2086 W, 240 V AC Halogen lamps: <= 739 W, 100 V AC Halogen lamps: <= 1700 W, 230 V AC Halogen lamps: <= 1773 W, 240 V AC Parallel compensated fluorescent lamp: <= 434 VA, 100 V AC Parallel compensated fluorescent lamp: <= 1000 VA, 230 V AC Parallel compensated fluorescent lamp: <= 1043 VA, 240 V AC Capacitive: , 10 A, 105 µF, 100...240 V AC
Local signalling	LED

### Environment

IP degree of protection	IP20
-------------------------	------

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Weight	1.01 kg
Package 1 Height	8 cm
Package 1 width	12.4 cm

Package 1 Length	27.8 cm
Unit Type of Package 2	S03
Number of Units in Package 2	6
Package 2 Weight	6.33 kg
Package 2 Height	30 cm
Package 2 width	30 cm
Package 2 Length	40 cm

## Offer Sustainability



Sustainable offer status	Green Premium product
REACH Regulation	<a href="#">REACH Declaration</a>
EU RoHS Directive	Compliant <a href="#">EU RoHS Declaration</a>
Mercury free	Yes
RoHS exemption information	Yes
China RoHS Regulation	<a href="#">China RoHS declaration</a> Product out of China RoHS scope. Substance declaration for your information
Environmental Disclosure	<a href="#">Product Environmental Profile</a>
Circularity Profile	<a href="#">End of Life Information</a>
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

## Contractual warranty

Warranty	18 months
----------	-----------

## Recommended replacement(s)

MTN649912 is replaced by the following group of products:

1x		SpaceLogic KNX Switch/Blind Master 8ch 10AX/16AC1 MTN6705-0008
1x		SpaceLogic KNX Switch/Blind Extension 8ch 10AX/16AC1 MTN6805-0008